




8Ω

LF Drivers - 12.0 Inches







- 500 W continuous program power capacity
 64 mm (2.5 in) copper voice coil
 50 3000 Hz response

- 98 dB sensitivity









PARAMETERS⁴

SPECIFICATIONS

| Nominal Diameter | 320 mm (12.0 in) |
|--|-------------------|
| Nominal Impedance | 8 Ω |
| Minimum Impedance | 6.3 Ω |
| Nominal Power Handling ¹ | 250 W |
| Continuous Power Handling ² | 500 W |
| Sensitivity ³ | 98.0 dB |
| Frequency Range | 50 - 3000 Hz |
| Voice Coil Diameter | 64 mm (2.5 in) |
| Winding Material | Copper |
| Former Material | Glass Fibre |
| Winding Depth | 13.0 mm (0.51 in) |
| Magnetic Gap Depth | 8.0 mm (0.31 in) |
| Flux Density | 1.15 T |

DESIGN

| Surround Shape | Double Roll |
|---|---|
| Cone Shape | Exponential |
| Magnet Material | Neodymium Inside Slug |
| Spider | Single |
| Pole Design | Straight Pole |
| Woofer Cone Treatment WP Waterproof Front Side | |
| Recommended Enclosur | re 40.0 dm ³ (1.41 ft ³) |
| Recommended Tuning | 64 Hz |

RCK12CL648

| Resonance Frequency | 52 Hz |
|---------------------|---|
| Re | 5.5 Ω |
| Qes | 0.32 |
| Qms | 4.3 |
| Qts | 0.3 |
| Vas | 64.0 dm ³ (2.25 ft ³) |
| Sd | 522.0 cm ² (80.9 in ²) |
| ηo | 3.4 % |
| Xmax | 4.5 mm |
| Xvar | 6.0 mm |
| Mms | 55.0 g |
| BI | 17.5 Txm |
| Le | 1.1 mH |
| EBP | 162 Hz |

MOUNTING AND SHIPPING INFO

| Overall Diameter | 313 mm (12.32 in) | |
|---|--------------------|--|
| Bolt Circle Diameter | 299 mm (11.77 in) | |
| Baffle Cutout Diameter | 282.0 mm (11.1 in) | |
| Depth | 133 mm (5.24 in) | |
| Flange and Gasket Thickn | ess 9 mm (0.35 in) | |
| Air Volume Occupied by Driver \$\$2.0 dm^3 (0.07 ft^3)\$} | | |
| Net Weight | 1.9 kg (4.2 lb) | |
| Shipping Units | 1 | |
| Shipping Weight | 2.8 kg (6.17 lb) | |
| Shipping Box | | |

360x360x200 mm (14.17x14.17x7.87 in)

2 hours test made with continuous pink noise signal within the range Fs-10Fs. Power calculated on rated nominal impedance. Loudspeaker in free air.
 2. Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 3. Applied RMS Voltage is set to 2.83 V for 8 ohms Nominal Impedance.
 4. Thiele-Small parameters are measured after a high level 20 Hz sine wave preconditioning test.

B&C Speakers s.p.a.

Via Poggiomoro, 1 - Loc. Vallina, 50012 Bagno a Ripoli (FI) - ITALY - Tel. +39 055 65721 - Fax +39 055 6572312 - mail@bcspeakers.com

SERVICE KIT